

# OKELVN



#### **BIP-39**

The BIP-39 word list contains 2048 unique words, each distinguishable by its first four letters. Therefore, only the first four letters of each seed phrase word need to be stored.

#### **Risk Disclosure:**

**Side-Channel Attack:** If the tile tray is not properly secured, attackers might analyze (count) the unused tiles to infer sensitive information, even without direct physical access, potentially compromising device security and leading to financial loss.

#### **Warning**

**Theft hazard:** Does not protect against theft or “Evil Maid” attacks.

#### **Notice**

**Damage risk:** Do not use power tools to tighten screws.

# °KELVN Quickstart Guide

## 1. Seed Phrase

Prepare seed phrase using the included worksheet. Only the first four letters of each BIP-39 word are needed. Use blank tiles for words with less than four letters.

## 3. Tiles

Insert tiles into the channel. Ensure words align within the numbered segments. Repeat until all words are assembled.

## 5. Reassembly

Apply a very small amount of anti-seize to threads of socket cap screws. Place the two halves with seed phrases facing each other and secure screws, finger tight only.

## 2. Disassembly

Remove the two screws to disassemble the body. Unscrew the right socket cap screw on the top row on one carrier using the included allen key by turning counter-clockwise. Remove the stopper.

## 4. Replace Stopper

Replace the stopper, apply a very small amount of anti-seize to threads and replace screw by turning clockwise till finger tight.

Torque to 4 in-lbs; ~ as tight as comfortable using the short end or the allen key

## 6. Label

Apply tamper-evident label, if desired.

